


S2B80 Series

Cyla 10



DIMENSIONS



W	H	X	BASE MODEL NO.
10"	96"	48"	S2B83-L48
10"	120"	72"	S2B85-L72
10"	120"	96"	S2B86-L96

SPECIFICATIONS

Drivers: 0-10V dimming to 1%, 120/277 for both Cylinder and Downlight (on separate circuits)

Mounting: Mounts to all Standard Electrical Junction Boxes (by others) with Hardware Provided

FEATURES

- Opal Matte Acrylic Cylinder
- Clear Silver Braided Cord with (1) Adjustable Aircraft Cable
- Downlight and Cylinder Core May Be Wired to Separate Control Circuits
- Drivers Mounted in Canopy
- LED 0-10V Dimming Driver

ORDER AS A COMPLETE UNIT:

Model No. + Downlight + Lamp Code + Finish + OA + Option Code

S2B83-L48	+ ____*	+ 27K	+ PT ZT	+ OA	+ Option
S2B85-L72	D18N	30K	BA CT		
S2B86-L96	D18M	35K	BB TT		
	D18W	40K	BN PWT		
			NT BST		
			GT CC		

____* = if left blank – no downlight

FINISHES

BA Brushed Aluminum **GT** Gold Touch **PWT** Pewter Touch
BB Brushed Brass **ZT** Bronze Touch **BST** Blackened Steel Touch
BN Brushed Nickel **CT** Copper Touch **CC** Custom Painted Finish
NT Nickel Touch **TT** Toffee Touch **PT** Powder Coated Finishes*

*(Specify Color Code from the list of Powder Coating Finishes)

DOWNLIGHT OPTIONS

D18N Narrow (30 degrees)
D18M Medium (45 degrees)
D18W Wide (60 degrees)

OPTIONS

BAC Buy America; Buy American Act; and Build America, Buy America Act Compliant.
EML Remote 10W Emergency LED Battery Backup
OA Specify Overall Height of Fixture in Inches; E.G. – OA48
1S Single Stem
BK1 Black Cord with (1) Adjustable Aircraft Cables
WH1 White Cord with (1) Adjustable Aircraft Cables

LUMENS

Cylinder Core Lighting Lumens: LXX = LED Wattage, therefore L24 = LED 24W. The typical lumen output is ~109LPW, so therefore L24 would deliver 2,616L. Use this formula to estimate delivered lumens based on the LXX number for each length.

Downlight Lumens: DxxW indicates Downlight wattage and beam spread. For the downlight, typical lumen output is 127LPW, so a D12W would deliver 1,524L in a wide beam pattern.

