





	DIMENSIONS				BASE MODEL NO.	ADD LAMP CODE	ADD FINISH CODE
	W	H	D	MC			
 	ADA	7"	18"	4"	9"	<b>S3860</b> 2N40 2C13E 1CF27	BA, BB, BC, BN, PT
		9"	24"	5-1/2"	12"	<b>S3861</b> 2N60 2C26E 2CF39	

**ORDERING INFORMATION**

Order as a Complete Unit: Model No. + Lamp Code + Finish Code + Option Code + Voltage

**TECHNICAL SPECIFICATIONS      FINISHES      OPTIONS**

<p><b>Ballast:</b> High Power Factor, Electronic, 120/277</p> <p><b>Mounting:</b> Wall Sconces Mount to a 4" Octagonal Electrical Box (by others) With a Universal Strap and Hardware Provided; Fixture Mounting Center (MC) Dimension is Measured from Top of Fixture to Center of Electrical Box</p>	<p><b>BA</b> Brushed Aluminum</p> <p><b>BB</b> Brushed Brass</p> <p><b>BC</b> Brushed Chrome</p> <p><b>BN</b> Brushed Nickel</p> <p><b>PT</b> Painted Finishes - (Specify Color Code from Our Standard Finish Chart)</p>	<p><b>EM</b> Emergency Battery Pack with Fluorescent Lighting (Remote)</p> <p><b>BTL</b> Bottom Lens</p> <p><b>DIM</b> Dimmable Integral Ballast (Consult Factory)</p> <p><b>FAA</b> Faux Alabaster Acrylic (Hand Painted)</p> <p><b>TPL</b> Top Lens</p> <p>Finish Combinations (Consult Factory)</p>
--	--	--

**LAMPING      FEATURES**

<p><b>N40</b> = 40 Watt A19 Incandescent</p> <p><b>N60</b> = 60 Watt A19 Incandescent</p> <p><b>C13E</b> = 13 Watt Quad Tube Compact Fluorescent 4 Pin Electronic, G24Q-1 Base</p> <p><b>C26E</b> = 26 Watt Quad Tube Compact Fluorescent 4 Pin Electronic, G24Q-3 Base</p> <p><b>CF27</b> = 27 Watt Biax Compact Fluorescent Electronic, 2G11 Base</p> <p><b>CF39</b> = 39 Watt Biax Compact Fluorescent Electronic, 2G11 Base</p>	<ul style="list-style-type: none"> <li>● Sandblasted Acrylic</li> <li>● Solid Bar Stock Material</li> </ul>
---	---